



## B7021HMCF - Size 1, Cutler-Hammer 3 Pole 3 Wire 30A Combo Starter 600V Coil

By Killark  
Catalog # B7021HMCF

Size 1, Cutler-Hammer 3 Pole 3 Wire 30A Combo Starter 600V  
Coil.



\*Representative Image

### Features

- Reset button provided as standard.
- Two control operator openings provided plugged as standard.
- Additional openings can be factory or field drilled.
- Copper-free (less than 4/10 of 1% copper) enclosure.
- Bolt on bi-directional ductile mounting lugs.

### General

Catalog Number	B7021HMCF
EU RoHS Indicator	Contact Manufacturer
Horsepower - Maximum	10
Series	B7
Size	1
UPC	783936096230

### Electrical Ratings

Coil Voltage	600V
Voltage Rating	600 V

### Certifications And Compliance

CSA File Number	LR11714
Hazardous Rating(s)	Class I, Divisions 1 & 2, Groups B, C, D
	Class I, Zones 1 & 2, Groups IIB+H2, IIA
	Class II, Divisions 1 & 2, Groups E, F, G
	Class III, Divisions 1 & 2
Nema Rating	3, 4, 4X
UL File Number	E83696

### Product Assets

[Catalogs - Killark Catalog](#)  
[Certifications - B7 Series Enclosure UL Certifications](#)  
[Customer Notices - Prop 65 Notice](#)  
[Installation Manuals - KIL\\_B7021 Series Mounting Pan IOM\\_K1057](#)



A Hubbell brand